

ZFP 1-8 LOOP NETWORKABLE ADDRESSABLE FIRE PANELS

Context
Plus



ZFP Standard Cabinet
(PART NUMBERS ON PAGE 8)



ZFP Medium Cabinet
(PART NUMBERS ON PAGE 8)



Compact Repeaters
(PART NUMBERS ON PAGE 8)



PICTURE a fire panel that is touchscreen-controlled, a breeze to install, provides clear and constant feedback on all aspects of system activity and is fully compliant with all relevant standards. Picture the ZFP - a powerful, intuitive and feature-rich range of 1 to 8 loop addressable fire panels from Context Plus.

Key Features

- ▶ Third-party certified to EN54 parts 2 and 4 by Intertek
- ▶ Communication protocol - Apollo XP95/Discovery
- ▶ Full compatibility with the Context Plus range of fire detectors, call points, sounders, beacons and control modules.
- ▶ Three cabinet sizes - standard (1, 2 or 4 loops), medium (2, 4, 6 or 8 loops) and large (2, 4, 6 or 8 loops)
- ▶ Full colour LCD touchscreen with an intuitive interface & digital QWERTY keyboard (touchscreen can be fully customised with a company logo)
- ▶ Secure fault tolerant network (needs separate network driver PCB)
- ▶ Up to 128 peer to peer node capacity (64 panels plus up to 64 Compact Controllers/Repeaters)
- ▶ Very flexible cause and effects
- ▶ Wide range of Switch & Indicator modules c/w slide-in labels for straightforward customisation. (Common word processor templates available online)
- ▶ Multiple "A-Bus" peripherals (I/O Units, Relays, Sounder Extender Cards, Conventional Zone Cards, etc)
- ▶ Programmable via galvanically isolated USB port
- ▶ Up to 200 separate zonal LEDs per panel (100 on standard sized cabinets)
- ▶ 10,000 programmable and indicatable detection zones
- ▶ Up to 38 characters of custom text per loop device
- ▶ Wide range of supported languages
- ▶ E-mailable firmware updates (no flash programmer required!)
- ▶ 20,000+ event memory (filterable by fire, fault and date)
- ▶ Automatic daylight saving (BST/GMT)
- ▶ 4 programmable operational modes
- ▶ Optional thermal printer with front-loading paper
- ▶ PC logging option for end-user
- ▶ 4 GB Micro SD memory simplifies off-site configuration
- ▶ Well-designed metal cabinets aid installation
- ▶ 20-way heavy duty brass earth bar(s) as standard
- ▶ 72-hour standby (plus 30 min alarm) in standard cabinets
- ▶ Powerful engineering and commissioning functions including 'SafeMode', 'DeviceManager' and more
- ▶ Powerful and intuitive PC programming tools
- ▶ Optional graphical interface solutions
- ▶ Up to 18Ah batteries in standard cabinets, 38Ah in larger cabinets.

Powerful
loop and battery
calculation tool
now available
online

ZFP 1-8 LOOP NETWORKABLE ADDRESSABLE FIRE PANELS

ZFP PART NUMBERS

Standard

ZFP PANELS WITH 40 ZONAL LEDs



Z015040NS/X/CON

ZFP 1 loop Panel with 40 zonal LEDs (Z47), 5A PSU.

Z025040NS/X/CON

ZFP 2 loop Panel with 40 zonal LEDs (Z47), 5A PSU.

Z045040NS/X/CON

ZFP 4 loop Panel with 40 zonal LEDs (Z47), 5A PSU.

Standard

ZFP PANELS WITH 40 ZONAL LEDs & ONBOARD PRINTER



Z025040PS/X/CON

ZFP 2 loop Panel with 40 zonal LEDs and on-board printer (Z49), 5A PSU.

Z045040PS/X/CON

ZFP 4 loop Panel with 40 zonal LEDs and on-board printer (Z49), 5A PSU.

Compact

ZFP REPEATERS, EXPANSION PCBs & GRAPHIC INTERFACES



ZREP1S

ZFP Repeater/Compact Controller. Surface mount. Requires BF360-24 1A 24V boxed PSU.

ZHN

ZFP RS485 Network PCB (one req. per main ZFP panel)

Z02LOOP/X

2 loop Extender PCB. (Extends 2 loop ZFP to 4 loops)

Medium

ZFP PANELS WITH 40 ZONAL LEDs



Z065040NM/X/CON

ZFP 6 loop Panel with 40 zonal LEDs (Z47), 5A PSU.

Z085040NM/X/CON

ZFP 8 loop Panel with 40 zonal LEDs (Z47), 5A PSU.

Medium

ZFP PANELS WITH 40 ZONAL LEDs & ONBOARD PRINTER



Z065040PM/X/CON

ZFP 6 loop Panel with 40 zonal LEDs and on-board printer (Z49), 5A PSU.

Z085040PM/X/CON

ZFP 8 loop Panel with 40 zonal LEDs and on-board printer (Z49), 5A PSU.

Miscellaneous

ZTOOLS ZFP programming tools (Windows)

Z11 4 Relay PCB (half size)

Z12 8 Relay PCB (full size)

Z13 8 Input output PCB (half size)

Z14 16 Input output PCB (full size)

Z15 4 x Conventional 1A 6K8 Sounder Circuit PCB (full size)

Z16 4 x Detection Zone & 2 x 1A 6K8 Sounder Circuit PCB (full size)



GRAPHICS PACKAGES

ZG1 ZFP Single Panel Graphics Interface Package

ZG2 ZFP 1 to 5 Panel Graphics Interface Package

ZG3 ZFP 1 to 5 Panel Graphics Interface Package with TCP/IP remote access manager

ZG4 ZFP 1 to 99 Panel Graphics Interface Package with TCP/IP remote access manager

Contact us for a full list of graphic package features

BEZELS, STAINLESS STEEL FRAMES & VISION WINDOWS - *Contact us for details.*

POWER SUPPLY & CHARGER

| | |
|---|---|
| Mains Supply Operating Voltage | 230Vac \pm 10% 50/60Hz 810mA max. |
| Rated current | 810mA Max (Standard cabinet ZFPs); 1.35A Max (Medium & Large Cabinet ZFPs) |
| Internal power supply | 5A (Standard cabinet ZFPs); 5A (Medium & Large Cabinet) |
| Max. continuous output current (incl. charging) | 5A (Standard cabinet ZFPs); 5A (Medium & Large Cabinet) |
| Max. VRLA battery size and type | 2 x 12V 18Ah (Standard cabinet ZFPs); 2 x 12V 38Ah (Medium & Large Cabinet) |

LOOP DRIVERS

| | |
|--|--|
| Number of loops | 1, 2, 4, 6 or 8 dependent on model |
| Max. output current per loop | 500mA (Voltage: 25V min; 34V max) |
| Communication Protocol | Context Plus XP95 (max. 127 addressable devices per loop) |
| Type of cable / Max. cable length per loop | Fire resistant screened, up to 2.5mm ² / 1KM max length |
| Max. allowable loop impedance/capacitance | 20 ohm (each conductor) |
| Max. cable capacitance | .27uF |

CONVENTIONAL SOUNDER CIRCUITS

| | |
|--|---|
| Number/type of conventional sounder circuits | 2 x 1A outputs. Protected by resettable overload circuit 19.5V min; 28V max |
| Output voltage | 19.5V minimum, 28V maximum |
| Type of cable / Max. cable length per loop | Fire resistant screened, up to 2.5mm ² / 1KM max length |

AUXILIARY INPUTS (PROGRAMMABLE)

| | |
|-------------------------------|--|
| Number of auxiliary inputs | 2 (Connect to 0V to trigger, Max. input voltage 27Vdc non-latching). 6800 ohm, 5% Tol, 0.25W |
| EOL resistor value (supplied) | 6800 ohm, 5% tolerance, 0.25W |
| Trigger resistor (supplied) | 470R, 0.25W |

RELAY OUTPUTS (PROGRAMMABLE)

| | |
|------------------------------|--|
| Number of relay outputs | 2 x programmable auxiliary relays; 1 x failsafe fault relay; 1 x 24Vdc aux. power output |
| Relay type & outputs | 1A, 30Vdc (maximum). Voltage free, single pole changeover |
| Fault relay | Active when faults are present or on total power failure |
| 24Vdc auxiliary power output | 19.5V minimum, 28V maximum. Max current 100mA. |

INDICATORS AND CONTROLS

| | |
|------------------------------------|--|
| Standard provision | All models include a Z41 Control module which comprises a full colour 4.3" touchscreen All mandatory EN54 indicators, 3 spare LEDs & a keyswitch allowing access to AL2 |
| Zonal Indicators | Up to 200 programmable LEDs available via Switch & Indicator expansion modules |
| Switches & onboard printers | Multiple switch & printer configs available via Switch & Indicator expansion modules |
| Switch & Indicator module capacity | 2 (standard cabinets); 4 (medium cabinets); 6 (large cabinets). 1 x Z41 req. per panel |

COMMUNICATION BUSES

| | |
|------------------------------------|---|
| On-board Serial Printer (Optional) | 1 x RS232 connector |
| Pager/DECT Interface | 1 x RS232 connector |
| Networking | 1 x RS485 connector (hi-integrity fault-tolerant) |
| Peripheral Bus (A-Bus) | 1 x RS485 connector. Allows the connection of up to 15 A-Bus PCBs. Wiring requirements = 2 core plus screen plus 2 core for power. |
| PC Interface | Galvanically isolated USB connector (provided on the Z41 Control/Display module) |

NETWORKING

| | |
|-----------------------------------|--|
| Network type | RS485 (hi-integrity fault tolerant, ring wired). 1xZHN PCB required per networked panel |
| Maximum no. of network nodes | 128 (up to 64 x 8 loop panels and 64 x compact controllers) |
| Type of cable / Max. cable length | Fire resistant screened, up to 2.5mm ² ; 1KM between nodes; 128KM (max network length) |
| Network wiring | Fire resistant screened cable, up to 2.5mm ² |
| Detail | Events (Fires, Faults, Disablements, Tests) & Actions (Silence/Resound Sounders, Reset) can be accepted over the network. Zones, Input & Output Groups, etc can be shared over the network |

MECHANICAL & ENVIRONMENTAL

| | |
|--|--|
| Finish & IP rating | Light grey texture (RAL7035) epoxy. Mild steel. Zintec 1.2mm |
| Operating temperature / humidity | -5°C to +40°C / 5% to 95 % R.H non condensing |
| Dimensions (lid & back box) H x W x D mm | |

